

Programmable DC Power Supply

MODEL: OPS-50100



Parameter			Specifications	
Output rating(@0℃ ~ 40℃)	Voltage		0 to 50 0 to 100	
Current utput WATT			5 KW	
Programming Accuracy			0.05% + 30mV	
(@25℃ ±5℃)±(%of output + offset)	Current		0.1% + 100mA	
Readback Accuracy	Voltage		0.05% + 20mV	
$(@25\% \pm 5\%)\pm (\% \text{ of output + offset})$	Current		0.1% + 100mA	
(@25 5 ±5 5)±(%51 6diput · 61166t)	Voltage		≤ 10mVp-p	
Ripple and Noise(20Hz to 20MHz)	Current		≤ 10mArms	
	Voltage		≤ 10mV	
Load Regulation (with V-Sensing)	Current		≤ 1mA	
	Voltage		≤ 10mV	
Line Regulation (with V-Sensing)	Current		≤ 1mA	
	Programming/Readback		≤ 250,W / ≤ 700,µA	
Resolution	Display Meter		1mV / 10mA	
Temperature Coefficient ±(%of output + offset) Voltage			0.01% + 5mV	
er a 30-minute warm-up Current		0.02% + 6mA		
Stability ±(%of output + offset)	Voltage		0.02% + 10mV	
After a 1 hour warm-up	Current		0.1% + 2mA	
·	-		Less than 50//s for output to recover to within 15mV following a change in output current	
Transient Response Time			from full load to half load or vice versa	
Voltage Programming Speed	Rising time		≤ 2V/ms	
	No load	Falling time	≤ 1V/ms	
		Rising time	≤ 1V/ms	
	Half load	Falling time	≤ 3V/ms	
Remote Sensing Capability	Voltage Drop		Up to 1V per each lead	
	Load Regulation		Add 5 mV to spec for each 1-volt change in the + output lead due to load current changes	
	Load Voltage		Subtract voltage drop in load leads from specified output voltage ratiing.	
	OVP		5% + 0.5V	
OVP and OCP Accuracy \pm (%of output + offset) OCP		5% + 10A	
	Activation Time		< 80ms when maximum output rating	
0	Power Switch ON/OFF		No overshoot, undershoot : ≤ -0.8V	
Output Voltage Overshoot & Undershoot	Voltage Output Setting		No overshoot, No undershoot	
Remote Interface			GPIB(IEEE-488.2) Option , RS232C Standard	
Programming Language		SCPI(Standard Commands for Programmable Instruments)		
Command Processing Time(average)	Apply		Setting	20ms
			Query	32ms
	Output Setting		Voltage & Current Setting	15ms
			Voltage & Current Query	32ms
	Measurement		Voltage & Current Query	32ms
	The Other		Setting & Query	< 35ms
State Storage Memory			Ten user-configurable(voltage,cu	rrent,OVP & OCP level)stored states
	Step(Voltage, Current,		Maximum 100 steps	
Cycling Mode	Slope & Delay time) Slope time		Osec ~ 86,400sec (24 hours)	
	Delay time		100ms ~ 86,400sec(24 hours)	
	Repeat		Maximum 15milion times	
Operation Temperature			0℃ ~ 40℃ for full rated output. At higher temperatures the output current is derated	
			linearly to 50% at 55°C maximum temperature	
Cooling				
Output Terminal Isolated (maximum, from chassis ground)			±60 Vdc when connecting shorting conductors without insulation to the (+)output to the (+)sense and the (-)output and the (-)sense terminals	
AC Input Ratings	Standard		단상 220V ± 10% 50~60Hz	
			3상 380V ± 10% 50~60Hz	
	Option		단상 100V ± 10% 50~60Hz	
	<u> </u>		단상 230V ± 10% 50~60Hz	
Colibration Interval	Precision		6 month	
Calibration Interval	Recommended		1 year	
Dimensions (19" Standard)			426mm(W) * 756mm(H) * 650mm(D)	
Maximum Input Power(full load)			12872W	
Weight	Net weight		166kg	
Weight	Gross weight		175kg	
 *상기모델은 사용자	Application	에 최적화하기위	해 예고없이 사양변경될 수 있으므로	